

DRC FOR H8 DSP FIRMWARE UPDATE

Powered by



V. 2.10

H8 DSP

DIGITAL INTERFACE PROCESSOR

HIGHLIGHTS

WHO NEEDS TO UPDATE THE FIRMWARE AND WHY?

WHO: Users with Hertz H8 DSP processor.

WHY: With this Firmware update for Audison DRC, compatibility with Hertz H8 DSP processor has been implemented.

WHICH ARE THE STEPS TO BE FOLLOWED TO UPDATE THE FIRMWARE?

IMPORTANT REMARK:

1. The steps of this upgrade must be performed strictly FOLLOWING THE SEQUENCE below
2. Pay utmost attention when performing the firmware upgrade and follow the warnings listed in the DRC firmware upgrade section of this document, to avoid damaging the product.
3. In order for the DRC to be upgraded, it must be connected to a **H8 DSP**.




WARNING: The firmware update procedure may be delicate. It is extremely important that it is performed under the best possible: if the firmware upgrade is launched but prematurely interrupted (e.g.: PC locked up, supply voltage drop to the **H8 DSP**, accidental disconnection of the USB cable during firmware upgrade), our After Sales Service might need to be contacted to reprogram the **H8 DSP**.

1. Connect your PC, using the USB cable, to the Hertz **H8 DSP** processor, where the Audison DRC has been plugged-in.
2. Supply power and turn on the **H8 DSP**, so that the DRC is on.
3. Launch the software "*DRC_Upgrade_R4_V2_10.exe*" contained inside the folder previously downloaded from the portal www.audisonbitdrive.eu
4. Select **H8 DSP** and then select **OK**.

5. The PC will synchronize with the DRC

Then click on:


- **DRC Upgrade to V2.xy** to update the device;
- **Quit**: to exit.




6. A warning pop-up dialog box will appear, indicating that you have to.

- close all running programs;
- disable any screen saver;
- disable energy saving modes;
- disable any anti-virus software.

Select **"YES"**.




7. Wait until the upgrade procedure is complete.



8. A pop-up dialog box showing the message "Upgrade completed" will appear

Select **"OK"**.



9. Select **Quit** to close the DRC Upgrade Software

