

audison

| prima

AP8.9 bit  
AP5.9 bit  
AP4.9 bit  
SOFTWARE  
UPGRADE

V. 2.2.0



ideato,  
progettato,  
ingegnerizzato  
in Italia

# Highlights

## WHO NEEDS TO UPDATE THE PC SOFTWARE AND WHY?

- WHO:**
- Users with AP8.9 bit where PC Software ver. **1.0.X.Y** is installed.
  - Users with AP8.9 bit AP5.9 bit or AP4.9 bit where a PC Software version lower than v. **2.2.0.x** is installed.


**WHY:** This PC Software update implements new functions.

## RELEASE NOTES v.2.2:

- Changed the default setting for the **"Sleep timeout for analogue input"** function from 20 min to OFF.
- Added SW audio muting when the stand-by mode is active.
- Disabled the input sensitivity sliders when the input channels are not connected.
- Fixed the wrong EQ + XO graph viewing when the SW is used with AP4.9 bit / AP5.9 bit.
- Fixed the wrong listening position viewing on the channel map when a reference point different from default setting is marked.

## ADDITIONAL NOTES:

- **AP bit extended compatibility:** The new PC SW ver. 2.2.0 manages AP8.9 bit, AP5.9 bit and AP4.9 bit.
- **Retro-compatibility with Setup files created with older PC SW ver. 1.0.X.Y:** the PC Software ver. 2.2.X.Y, launched in online mode (with AP bit connected), can load Setup files created with previous PC SW ver 1.0.X.Y. The settings loaded that way in the AP bit device can be saved again, getting the file automatically updated to ver. 2.2.X.Y.
- **Controlled Bass-Boost:** it is a function to stress low and mid-low frequencies; it can be enabled both through the DRC and through the PC SW. It can be graphically adjusted through the PC SW. It provides the ability to add 2 adjustable parametric poles: one acting on the subwoofers and the other on the woofers.



- **Preferential Memory:** through the PC SW you can associate a preset memory to a certain input (ex. MASTER, OPTICAL or AUX); by selecting that input, also the memory associated to it will be automatically selected.
- **Load memory from "File" function:** you can load one single memory from "File" and copy it into one of the 2 memories of the AP bit device.
- **Muted head unit signal:** in presence of gongs signals on the MASTER input while playing the AUX or OPTICAL input, the device will automatically take the input back to the MASTER input. When the signal generated by the vehicle ends, playback moves back to the previously selected source.

**Remark:** to use this feature, the head unit has to be on MUTE mode.

## - New input channels configuration:

2way F + AUX	2way F + SUB L/R	F + R + SUB
2way F + R	F + AUX	F + R + SUB L/R
2way F + SUB	F + R + AUX	F + R + C + SUB

- **DERIVE SUB from function:** if an input configuration without subwoofer input has been selected, you can choose the channels (FRONT+REAR; REAR; FRONT) from which you wish to build the subwoofer frequency response.


- **New default value:** The default parameters of the "Settings" menu have been updated.

- **"Check for updates on startup" function:**

When you launch the PC SW with an AP bit product connected to the PC (with the Internet connection already activated), the PC SW will automatically look for updates on the Audison bit Drive Portal, notifying the user if any is available.

This function is active by default.

- **Help Online:** The "Help Online" sections for AP5.9 bit and AP4.9 bit have been updated
- **Language pack:** Italian/Russian/Korean/Japanese/German, selectable with the PC SW through the "File -> Preferences" menu.



## WHAT ARE THE NEW PC SW ver 2.2.X.Y COMPATIBILITIES?

**WARNING:** All PC SW versions 2.2.X.Y are exclusively compatible with all FW versions 2.2.X.Y and vice versa.



So, once the present PC SW update has been completed, you'll have to update the FW of your AP bit device.

### IMPORTANT REMARKS:

- It is not possible to install two different PC SW versions in the same PC
- It is not possible to use the PC SW ver. 2.2.X.Y on AP 8.9 bit with FW ver. 1.0.X.Y

The PC SW will display the following alert message:



In that case it is possible:

- To go on with the FW ver. 2.0.0.2 update (ex. new AP8.9 bit)
  - To use the PC SW ver. 1.0.X.Y (ex. AP8.9 bit previously installed and setup) to connect the AP bit device; then, save the Setup file (.aps) as described in the following section, point 1. **"SAVING SETUP FILE (optional)"**.
- It is possible to use the PC SW ver. 2.2.0.X.Y, both in **Offline** mode (no device connected) and in **Online** mode (ex. AP8.9bit with FW 2.2.X.Y and connected), to read, modify and save the Setup files (.aps) previously created with PC SW ver. 1.0.X.Y.

The PC SW will display the following alert message:



If you save, the Setup file (.aps) will be automatically converted to work exclusively with the PC SW versions 2.2.X.Y.

## WHAT ARE THE STEPS TO UPGRADE THE PC SOFTWARE?

### 1. SAVING SETUP FILE (optional)

If your product is already installed and set up, remember to save the Setup file (.aps) using a compatible PC SW version.

**WARNING:** More specifically, if you want to update an **AP8.9 bit**, where SW/FW **ver. 1.0.X.Y** has been previously installed and configured, you need to:

- Save the Setup file (.aps) using exclusively the PC SW ver. 1.0.X.Y;
- Now you can perform the present PC SW and FW ver. 2.2.X.Y update;
- Once the update has been completed, open the PC SW, load the previously saved Setup file (.aps), then save the Setup file again to convert it automatically.

**Remark:** it won't be possible to use that Setup file anymore with PC SW versions 1.0.X.Y.

If your AP bit product is new, got to step 2.

### 2. UNINSTALLING the AP bit PC Software (currently installed on the PC).

#### Procedure 1

To uninstall AP bit PC software you can use the link in the menu:

**Start / All programs / AP bit / uninstall**



#### Procedure 2


To uninstall AP bit PC software, you can also use the standard procedure:

**Start / Control Panel / Uninstall or change a program / AP bit / remove.**

### 3. INSTALLING the AP bit PC Software v. 2.2.0.X


#### 1) Windows XP, Windows Vista, Windows 7, Windows 8, 8.1, Windows 10:

Open the folder "AP bit SW\_v. 2.2.0". Locate the "APbit-installer" icon and double click on it:




#### 2) Windows XP, Windows Vista, Windows 7, Windows 8, 8.1, Windows 10:


Read the **LICENSE AGREEMENT** before proceeding with the installation. Select **NEXT** to accept the terms and continue with the installation or **CANCEL** to interrupt it;



- 3) **Windows XP, Windows Vista, Windows 7, Windows 8, 8.1, Windows 10:** Select:
- **INSTALL** to proceed with the installation;
  - **BACK** if you wish to return to the previous page;
  - **CANCEL** to exit installation



- 4) **Windows XP, Windows Vista, Windows 7, Windows 8, 8.1, Windows 10:**  
Select **CLOSE** to complete the installation.



[www.audison.eu](http://www.audison.eu)

**audison**  
ISTINTO  
INNOVATIVO

**PART OF ELETTRONEDIA**  
62018 Potenza Picena (MC) Italy  
T +39 0733 870 870 - F +39 0733 870 880  
[www.elettromedia.it](http://www.elettromedia.it)